UNCLASSIFIED

AD 433172

DEFENSE DOCUMENTATION CENTER

FOR

SCIENTIFIC AND TECHNICAL INFORMATION

CAMERON STATION, ALEXANDRIA, VIRGINIA

UNCLASSIFIED

64-10

433172

Log Periodic Dipole Array with Parasitic Elements

NORMAND BARBANO

DDC

MAR 30 1964

TISIA B

SYLVANIA ELECTRONIC SYSTEMS
Government Systems Management
for GENERAL TELEPHONE & ELECTRONICS

GENERAL SYSTEM

ELECTRONIC DEFENSE LABORATORIES

MOUNTAIN VIEW, CALIFORNIA

PREPARED FOR THE UNITED STATES ARMY

U S ARMY ELECTRONICS RESEARCH UNIT
POST OFFICE BOX 205
MOUNTAIN VIEW, CALIFORNIA

DISTRIBUTION LIST FOR EDL PUBLICATION: M 623

COMMANDING OFFICER
US ARMY ELECTRONICS RESEARCH UNIT
P O BOX 205
MOUNTAIN VIEW, CALIFORNIA   1D1

COMMANDING GENERAL
US ARMY MATERIEL COMMAND
ATTN: AMCRD-DE-E-E
WASHINGTON 25, D. C.   2D1

TECHNICAL LIBRARY, OASD-R&D
ROOM 3E1C65, THE PENTAGON
WASHINGTON, D. C.   20390   3D1

COMMANDING OFFICER
HARRY DIAMOND LABORATORIES
ATTN: LIBRARY
WASHINGTON 25, D. C.   4D1

CHIEF OF NAVAL OPERATIONS
DEPARTMENT OF THE NAVY
ATTN: OP 347
WASHINGTON 25, D. C.   5D1

CHIEF, BUREAU OF SHIPS
DEPARTMENT OF THE NAVY
ATTN: CODE 818
WASHINGTON 25, D. C.   6D1

CHIEF
BUREAU OF WEAPONS, RAAV
DEPARTMENT OF THE NAVY
WASHINGTON, D. C.   20390   7D1

CHIEF
BUREAU OF NAVAL WEAPONS
DEPARTMENT OF THE NAVY
ATTN: CODE R-12
WASHINGTON, D. C. 20390   8D1

OFFICE OF NAVAL RESEARCH
DEPARTMENT OF THE NAVY
ATTN: CODE 427
WASHINGTON, D. C. 20390   9D1

DIRECTOR
US NAVAL RESEARCH LABORATORY
ATTN: CODE 2027
WASHINGTON, D. C.   20390   10D1

CENTRAL INTELLIGENCE AGENCY
ATTN: OCR MAIL ROOM
WASHINGTON, D. C. 20505   11D2

CHIEF OF STAFF
US AIR FORCE
ATTN: DCS/D AFOP-OO
WASHINGTON 25, D. C.   12D1

CHIEF OF STAFF
US AIR FORCE
ATTN: AFRSTB
WASHINGTON, D. C.   20390   13D1

DEPUTY C/S FOR MILITARY OPNS
DEPARTMENT OF THE ARMY
ATTN: ORGN R&D BRANCH
WASHINGTON, D. C.   20390   14D1

DIRECTOR
US NAVAL RESEARCH LABORATORY
COUNTERMEASURES BRANCH
CODE 5430
WASHINGTON 25, D. C.   15D1

CENTRAL INTELLIGENCE AGENCY
ATTN: LIAISON DIV, OCD
2430 E STREET NW
WASHINGTON 25, D. C.   16D1

US ATOMIC ENERGY COMMISSION
DIVISION OF MILITARY APPLICATION
ATTN: CLASSIFIED TECH LIBRARY
1901 CONSTITUTION AVE., NW
WASHINGTON 25, D. C.   17D1

CHIEF OF RESEARCH & DEVELOPMENT
OCS, DEPARTMENT OF THE ARMY
WASHINGTON 25, D. C.   18D1

CHIEF, US ARMY SECURITY AGENCY
ARLINGTON HALL STATION
ARLINGTON 12, VIRGINIA   19D1

DEPUTY PRESIDENT
US ARMY SECURITY AGENCY BOARD
ARLINGTON HALL STATION
ARLINGTON 12, VIRGINIA   20D1

DEFENSE DOCUMENTATION CENTER FOR
SCIENTIFIC & TECHNICAL INFO-DDC
CAMERON STATION
ALEXANDRIA, VIRGINIA   21D20

CHIEF
US ARMY SECURITY AGENCY
ATTN: IALOG-ESE
ARLINGTON HALL STATION
ARLINGTON 12, VIRGINIA   22D1

COMMANDING OFFICER
USA FOREIGN SCIENCE & TECHNOLOGY CENTER
ATTN: AMXST-PP-CB
MUNITIONS BUILDING
WASHINGTON, D. C.   20315   23D1

COMMANDER
TACTICAL AIR COMMAND REGION
LANGLEY AFB, VIRGINIA   24D1

DIRECTOR
NATIONAL SECURITY AGENCY
ATTN: C3/TDL
FORT GEORGE G. MEADE, MARYLAND
          25D2

COMMANDER
AF CAMBRIDGE RESEARCH LABORATORY
ATTN: CRREL
HANSCOM FIELD
BEDFORD, MASSACHUSETTS   26D1

COMMANDING OFFICER
US ARMY ELECTRONICS R&D LABORATORIES
ATTN:SELRA/ADJ
FORT MONMOUTH, NEW JERSEY   27D1

COMMANDING OFFICER
US ARMY ELECTRONICS R&D LABORATORIES
ATTN: SELRA/GFR
FORT MONMOUTH, NEW JERSEY   28D1

COMMANDING OFFICER
US ARMY ELECTRONICS R&D LABORATORIES
ATTN: SELRA/SE
FORT MONMOUTH, NEW JERSEY   29D1

MARINE CORPS LIAISON OFFICER
ATTN: SELRA/LNR
U S ARMY ELECTRONICS R&D LABORATORIES
FORT MONMOUTH, NEW JERSEY   30D1

COMMANDING OFFICER
US ARMY ELECTRONICS MATERIEL SUPPORT
AGENCY, ATTN: SELMS/ES-ADJ
FORT MONMOUTH, NEW JERSEY   31D1

COMMANDING GENERAL
US ARMY ELECTRONICS COMMAND
ATTN: AMSEL-EW
FORT MONMOUTH, NEW JERSEY   32D1

COMMANDER
ROME AIR DEVELOPMENT CENTER
ATTN: RAALD
GRIFFITHS AFB
ROME, NEW YORK   34D1

REDSTONE SCIENTIFIC INFO CENTER
US ARMY MISSILE COMMAND
REDSTONE ARSENAL, ALABAMA   35D5

AIR FORCE MISSILE TEST CENTER
AFMTC-MTBAT
PATRICK AFB, FLORIDA   36DC1

AIR FORCE MISSILE TEST CENTER
AFMTC TECH LIBRARY-MU 135
PATRICK AFB, FLORIDA   37Du1

18 MARCH 1964

CONTINUED ON REVERSE SIDE

COMMANDER
AIR PROVING GROUND COMMAND
ATTN: APGC-PGAPI
EGLIN AFB, FLORIDA   38D1

COMMANDER
AERONAUTICAL SYSTEMS DIVISION
AIR FORCE SYSTEMS COMMAND
ATTN: ASRNCC-1
WRIGHT-PATTERSON AFB, OHIO   39D1

COMMANDER
WRIGHT AIR DEVELOPMENT DIVISION
ATTN: WWRNRE-4
WRIGHT-PATTERSON AFB, OHIO   40D1

COMMANDER
WRIGHT AIR DEVELOPMENT DIVISION
AERONAUTICAL SYSTEMS DIVISION
ATTN: ASRNRE-4
WRIGHT-PATTERSON AFB, OHIO   41D1

COMMANDER
WRIGHT AIR DEVELOPMENT DIVISION
ATTN: ASRNCFI
WRIGHT-PATTERSON AFB, OHIO   42D2

PRESIDENT
US ARMY AIR DEFENSE BOARD
ATTN: IDRS
FORT BLISS, TEXAS   44D1

DIRECTOR
COMMUNICATIONS & ELECTRONICS
AIR DEFENSE COMMAND
ENT AIR FORCE BASE
COLORADO SPRINGS, COLORADO   45D1

COMMANDER
AF MISSILE DEVELOPMENT CENTER
ATTN: MISSILE COUNTERMEASURES
LABORATORY HDLV
HOLLOMAN AFB, NEW MEXICO   46D1

COMMANDING OFFICER
US ARMY ELECTRONICS R&D ACTIVITY
ATTN: SELWS/W
WHITE SANDS MISSILE RANGE, N.M.   47D1

COMMANDER, FIELD COMMAND
DEFENSE ATOMIC SUPPORT AGENCY
AIR DEVELOPMENT DIVISION
SANDIA BASE
ALBUQUERQUE, NEW MEXICO   48D1

COMMANDING OFFICER
US ARMY ELECTRONICS R&D ACTIVITY
ATTN: SELHU-EE
FORT HUACHUCA, ARIZONA   50D1

COMMANDING GENERAL
US ARMY ELECTRONICS PROVING GROUND
ATTN: AG TECHNICAL LIBRARY
FORT HUACHUCA, ARIZONA   51D1

COMMANDER
PACIFIC MISSILE RANGE
ATTN: LIBRARIAN
POINT MUGU, CALIFORNIA   52D1

COMMANDER
NAVAL ORDNANCE TEST STATION
ATTN: TEST DIRECTOR - CODE 30
INYOKERN, CHINA LAKE, CALIFORNIA   53D1

COMMANDING OFFICER & DIRECTOR
US NAVY ELECTRONICS LABORATORY
SAN DIEGO 52, CALIFORNIA   54D1

STANFORD ELECTRONICS LABORATORY
STANFORD UNIVERSITY
ATTN: W. R. RAMBO
STANFORD, CALIFORNIA   55D1

SCIENTIFIC & TECHNICAL INFO FACILITY
ATTN: NASA REP (SAK/DL-925)
P O BOX 5700
BETHESDA, MARYLAND 20014   56D1

COMMANDING OFFICER
US ARMY COMBAT DEVELOPMENTS COMMAND
COMMUNICATIONS - ELECTRONICS AGENCY
ATTN: CAGCE-ESE
FORT HUACHUCA, ARIZONA   57D1

DIRECTOR
USA ENGINEER GEODESY INTELLIGENCE AND
    MAPPING R&D AGENCY
ATTN: ENGGM-SS
FORT BELVOIR, VIRGINIA   58D1

ELECTRONIC DEFENSE LABORATORIES

P. O. BOX 205

Mountain View, California

TECHNICAL MEMORANDUM
No. EDL-M623
30 January 1964

LOG PERIODIC DIPOLE ARRAY WITH PARASITIC ELEMENTS

Normand Barbano

Approved for Publication .... B. Lamberty
Manager
Antenna Department

K. Walton
Head
Antenna Systems Section

SYLVANIA ELECTRIC PRODUCTS, INC.

CONTENTS

ILLUSTRATIONS

ILLUSTRATIONS -- Continued

LOG PERIODIC DIPOLE ARRAY WITH PARASITIC ELEMENTS

Normand Barbano

1. ABSTRACT.

The design and measured characteristics of dipole
and monopole versions of a log periodic array with
parasitic elements are discussed. In a dipole array
with parasitic elements, these elements are used
in place of every alternate dipole, thereby elimina-
ting the need of a twisted feed arrangement for the
elements to obtain log periodic performance of the
antenna. This design with parasitic elements lends
itself to a monopole version of the antenna which has
a simplified feeding configuration. The result is a
log periodic antenna design that can be used from
high frequencies through microwave frequencies.

2. INTRODUCTION.

This report concerns modifying the design of a log periodic dipole antenna
fed in phase progression such that the antenna will produce backfire radia-
tion and operate in a pseudofrequency independent manner. The modification
consists basically of replacing every alternate dipole element with a para-
sitic element of the same length. The resulting configuration is a log
periodic dipole array which incorporates driven and parasitic elements with
the same design ratio, τ, and element-spacing-to-element-length ratio, s/ℓ,
as the initial antenna.

The characteristics of the modified antenna are discussed below, along with
results of measurements taken on antenna models using one or two parasitic
elements per cell. It is shown that the dipole array images exactly over a
perfect ground plane to form a log periodic monopole array with parasitic
elements. Special tuning networks or transmission-line coupling networks
are shown to be unnecessary with this monopole array. Using measured
data, the antenna's performance is discussed.

- 1 -

3. _____ GENERAL DISCUSSION.

Co-planar log periodic dipole arrays have been in existence since 1960,
when D. E. Isbell published an article illustrating a method of feeding the
elements of the array in a phase reversal rather than a phase progression
manner.[1] This phase reversal method of feeding the structure resulted in
a log periodic array with pseudofrequency independent characteristics.
The radiation patterns are unidirectional and linearly polarized in the
direction of the dipoles. The beamwidths are constant over the entire
bandwidth of the antenna. The input impedance is nearly constant with
frequency.

Figure 1 illustrates the two methods of feeding the log periodic dipole array:
phase progression and phase reversal. In the first method, the elements on
one side of the structure are attached to one side of the two-wire trans-
mission-line feeder, and the other elements are attached to the second wire
of the transmission-line feeder. Since these elements are closely spaced,
the phase of the current in adjacent elements will progress along the
structure with respect to the feed, as shown in Figure 1A. A lagging phase
condition is set up along the structure, with the result that a forward wave
is excited and end-fire radiation occurs.

When the method of feeding the structure by phase reversal is employed,
the result is backfire radiation. From Figure 1B, it can be seen that by
alternately connecting each adjacent element to the opposite side of the
transmission-line feeder, a phase reversal of π radians is introduced be-
tween each element. A backward wave can now be supported, since a leading
phase condition exists along the structure with respect to the feed. This
backward wave causes the backward radiation from the antenna.

Since the conception of the log periodic dipole antenna, the use of the
Brillouin diagram for analyzing periodic structures has been extended to
log periodic antennas.[2,3,4] The Brillouin diagram shows the relationship
of the phase constant on a periodic structure, β, to the intrinsic phase
constant of free space, k, such that

$$\beta = \frac{2\pi}{\lambda_g} , \qquad (1)$$

and

$$k = \frac{2\pi}{\lambda_o} , \qquad (2)$$

_____

1. See list of References in Section 8.

A. PHASE PROGRESSION METHOD

B. PHASE REVERSAL METHOD

Figure 1. Two Methods of Feeding an Array of Log Periodic Dipoles.

3.   -- Continued.

     where λ_g = wavelength of the bound wave on the
                              uniform structure, and

               λ_o = free-space wavelength.

The k-β version of the Brillouin diagrams for the two methods of feeding
an array of log periodic dipoles is shown in Figures 2A and 2B. [5, 6]
These plots are normalized with respect to the distance, d, along a unit
cell of a uniform structure. The k-β diagram for the uniform structure
using the phase progression method of feeding the dipoles is shown in
Figure 2A. The dashed curve shows the variation of kd versus βd.
Note that β is always positive. This indicates that a lagging phase con-
dition prevails on the structure relative to the feed point for all frequen-
cies. Therefore, the wave on the structure propagates in the forward
direction, and only end-fire radiation can be expected to occur. In
contrast, the diagram for the uniform dipole structure fed with the
phase reversal method shows a region where β is negative (Figure 2B).
In this region of the diagram, the phase along the structure relative
to the feed is leading. A backward wave will be supported and backfire
radiation will occur. The region between the 45-degree slopes(kd=$\pm\beta$d)
drawn in the figures indicates where the wave on the structure is loose-
ly bound. It is within this region that radiation is most likely to occur
on a log periodic structure. These diagrams serve to verify the earli-
er conclusions made about the two methods of feeding the log periodic
dipole arrays.

DESIGN PARAMETERS.

For reference, the parameters used in the design of a log periodic
dipole antenna are now discussed. The structure is completely defined
by the geometric ratio, τ, and the element-spacing-to-element-length
ratio, s/ℓ. As apparent in Figure 3, the geometric ratio gives the
growth rate of the elements and spacings by the following relationships:

$$\tau = \frac{\ell_n}{\ell_{n+2}} = \frac{x_n}{x_{n+2}} , \qquad (3)$$

or

$$\sqrt{\tau} = \frac{\ell_n}{\ell_{n+1}} = \frac{x_n}{x_{n+1}} , \qquad (4)$$

where x_n is the distance from the apex of the antenna to the nth element.

A. k-β DIAGRAM FOR ANTENNA USING PHASE PROGRESSION METHOD

B. k-β DIAGRAM FOR ANTENNA USING PHASE REVERSAL METHOD

Figure 2.   k-β Diagram for the Two Methods of Feeding an Array of Log Periodic Dipoles.

Figure 3.   Parameters Used to Define a Log Periodic Dipole Array.

3.   --   Continued.

The element-spacing-to-element-length ratio is given by

$$\frac{s_n}{\ell_n} = \frac{(1 - \sqrt{\tau})}{2 \tan \frac{\alpha}{2}}, \tag{5}$$

where α is the included angle at the apex of the structure.   Therefore,

$$\alpha = 2 \tan^{-1} \frac{\ell_n}{2 x_n}. \tag{6}$$

The largest and smallest values of ℓ_n limit the bandwidth of the antenna -- the lowest frequency by the longest element and the highest frequency by the shortest element.   The structure can be truncated at both ends without caus-ing any serious degradation of antenna performance.   Different values of τ will change the radiation pattern characteristics somewhat.[7]   A high value will give a narrower E-plane and H-plane radiation pattern beamwidth, a higher gain, and a larger front-to-back ratio.   The impedance increases with a smaller value of τ and angle α.

4. UNIFORM DIPOLE ARRAY WITH PARASITIC ELEMENTS.

As a preliminary examination of the log periodic dipole array with parasitic elements, consider a uniform array of driven and parasitic elements, as illustrated in Figure 4. Its construction consists of a two-wire transmission-line feeder with the dipole elements connected in a fashion similar to that shown in Figure 1A (the phase progression method of feeding a log periodic dipole array). The input to the feeder is electrically balanced. Parasitic elements are placed between the dipole elements to obtain a current phase reversal of π radians from one element to the next. This phase reversal is a primary requirement for obtaining a pseudo frequency-independent operation of the antenna.

A uniform dipole array with parasitic elements 24 inches long was constructed to determine its Brillouin (k-β) diagram and radiation patterns associated with the diagram. This structure, shown in Figure 5, has resonant elements near 490 Mc. An element spacing of 2.4 inches (0.1λ at 490 Mc) was used. This array was designed to have a 50-ohm input impedance at the design frequency. The characteristic impedance of this uniform array was found to be dependent primarily upon the transmission-line feeder characteristics and also upon the element-spacing-to-element-length ratio, s/ℓ.

Near-field phase measurements for the k-β diagram were taken along the feeder transmission line of the structure over the frequency range of 50 to 1000 Mc, and radiation patterns were measured over the corresponding frequency range. From these measurements, the phase constant, β, is determined. If a unit cell on the structure is defined to be the region from one driven element to the next along the feeder line, then the Brillouin diagram can be normalized in terms of a unit cell distance, d. The diagram for the uniform structure is shown in Figure 6 as having the normalized coordinates, kd and βd. This diagram contains a few of the measured E-plane radiation patterns at discrete frequencies.

The Brillouin curve begins at the origin at zero frequency and extends through the forward wave region, $0 \leq \beta d \leq \pi$, with increasing frequency. In this region, the phase along the feeder line lags the reference phase at the input terminals, and end-fire radiation occurs as shown by the radiation patterns. As the curve approaches the boundary, $\beta d = \pi$, radiation in both the end-fire and backward directions occurs, indicating that both the forward and backward waves are excited on the structure. The curve now extends into the backward-wave region, $\pi \leq \beta d \leq 2\pi$, where a leading phase distribution exists on the feeder line. Backward-wave radiation now occurs as shown in Figure 6. In the region where kd $\geq -(\beta d - 2\pi)$, the surface wave on the structure is loosely bound; however, the wave is tightly bound in the region where kd $\leq -(\beta d - 2\pi)$. The curve then proceeds to cross the

Figure 4.   Uniform Dipole Array with Parasitic Elements.

63091801

Figure 5.   Model of a Uniform Dipole Array with Parasitic
Elements ($s/\ell = 0.2$).

Figure 6.   Brillouin Diagram for Uniform Dipole Array with
Parasitic Elements (s/ℓ = 0. 2).

4.   -- Continued.

boundary, $\beta d = 2\pi$, into the forward-wave region, $2\pi \leq \beta d \leq 3\pi$. The wave is still loosely bound in this region. At the intersection with the line, $\beta d = 2\pi$, radiation in both the end-fire and backward directions occurs once again on the structure, as shown in Figure 6. The region, $2\pi \leq \beta d \leq 3\pi$, is then entered, and end-fire radiation occurs once again with the wave tightly bound.

The Brillouin diagram shows that a log periodic dipole array with parasitic elements is capable of stable, pseudo frequency-independent operation. A Brillouin diagram for a particular uniform array can be used to predict the performance of other similar arrays, provided the element-length-to-element spacing, s/ℓ, is kept constant. This constancy is achieved by scaling the coordinates, kd and βd, to compensate for the difference in the element lengths.

The active region of a log periodic antenna occurs where the electrical length of the elements is nearly a half-wavelength; thus it can be seen that the k-β diagram of a uniform array with elements of equivalent length predicts that backfire-radiation will most likely occur at this frequency. For example, if a log periodic array having an s/ℓ ratio of 0.2 is fed with a 490-Mc signal, then the diagram of Figure 6 will apply. It is apparent that the points on the curve corresponding to this frequency lie in the backward-radiation region of the diagram. A close investigation of the frequency band-width in the radiation region of Figure 6 shows that it is narrower than that of a conventional log periodic dipole antenna. This indicates that the equivalent circuit for the active region of the dipole array with parasitic elements has a higher effective Q. From this information, it can be predicted that a higher density of elements (a larger value of τ) is required for the log periodic dipole array with parasitic element design than for the conventional dipole array design. As will be seen below, this requirement becomes necessary for successful operation of the antenna.

wait

5.   <u>LOG PERIODIC DIPOLE ARRAY WITH PARASITIC</u>
                                      <u>ELEMENTS.</u>

5.1   <u>Single Parasitic Element Design.</u>

A log periodic dipole array with a single parasitic element will be considered in this section. The antenna is a co-planar type antenna designed such that each alternate element can be considered to be a driven element, with parasitic elements located in between these driven elements. The design parameters for this structure, τ and s/ℓ, are identical to a conventional log periodic dipole array. The variables used with these parameters are defined in Figure 7. The antenna utilizes a two-wire transmission-line feeder with a balanced input, with the input being located at the end having the shortest elements. The driven elements are connected to the feeder line, and the parasitic elements are unattached, as described in the discussion on the uniform array. The length and spacing between each adjacent element is a function of the geometric ratio, τ, and the element-spacing-to-element-length ration, s/ℓ, as given by Equations (3) and (5), respectively.

The parasitic elements essentially are located at the position normally occupied by the active elements that connect to the opposite sides of the transmission line in a conventional log periodic dipole array. The parasitic elements produce the same effect as the driven dipole elements that they replace; that is, they introduce a constant phase shift of π radians between elements. A parasitic element, when located in the active region of the antenna, receives its energy primarily by the mutual coupling between it and the active elements. To some extent, mutual-coupling effects also exist between parasitic elements. Energy is not coupled to the parasitic elements capacitively from the feeder line. To verify this, experiments were performed in which the spacing between the parasitic elements and the transmission-line feeder was varied. No evidence of capacitive coupling was noted, since the experimental results showed negligible changes in the antenna characteristics.

Several models of the dipole array with parasitic elements were constructed for evaluation. These antennas were found to have a pseudofrequency independent operation. Their radiation patterns have constant beamwidths, and their input impedance is nearly constant over the entire frequency range of the antennas. It was noted that on models having too low a value of τ and angle α, the antenna ceased to function in a pseudo frequency-independent manner. With large element spacings, the mutual coupling between the parasitic elements and the active elements is reduced to a value below which the reradiated energy from the parasitic element is insufficient to act as an equivalent source. When the antenna operates properly, it behaves as if its apparent phase center moves along the structure with frequency such that, over a period, the phase

Figure 7.   Parameters Used to Define a Log Periodic Dipole Array
with Parasitic Elements.

5.1   -- Continued.

center will change continuously and smoothly from the driven element to the
parasitic element, and finally to the next driven element.

A model of the dipole array with parasitic elements which has the design
parameters, τ = 0.898 and s/ℓ = 0.113, is shown in Figure 8. The shortest
element of the structure (an active element) is 5.60 inches long, and the long-
est element (a parasitic element) is 12.54 inches long. The antenna is fed
with an infinite balun constructed in one of the transmission-line feeders. A
coaxial line with a characteristic impedance of 50 ohms was used.

The impedance characteristics of this antenna over a full period are shown
in Figure 9. The impedance circles approximately 25 ohms with a VSWR of
2:1 over the frequency range of 600 to 700 Mc. The low value of impedance
occurs because of the number proximity of the parasitic element to the dri-
ven element. This effect is similar to that experienced with a dipole antenna
having a driven and a reflecting parasitic element.

The radiation power patterns in the plane of the electric field are shown in
Figure 10. These patterns have essentially a constant beamwidth of 60
degrees and a front-to-back ratio of 15 db or better. The radiation patterns
are well-behaved over the frequency bandwidth of the antenna, as evident in
Figure 10, and no radiation pattern degradation is experienced because of
the parasitic elements in this antenna design.

5.2   Multiparasitic Element Design.

The next logical development of the log periodic dipole antenna with parasitic
elements is a model having more than one parasitic element in a cell (a cell
being defined in this case as the distance from one driven element to the next
adjacent driven element). To investigate this interesting possibility, a dipole
array with only a single parasitic element, and having the design parameters,
τ = 0.9 and s/ℓ = 0.201, was constructed. This antenna was tested and
found to work satisfactorily in accordance with the behavior described in
Section 5.1.

The next experiment involved modifying this antenna by adding to it a second
complete set of parasitic elements. These elements were cut to the same
length as the existing parasitic elements and placed on the antenna such that
there were two parasitic elements of the same length between the driven
elements or cells. The relative spacing of these elements in each cell was
varied by the same percentage to obtain the best impedance and radiation
characteristics of the antenna. The best design resulted in a spacing for the

63060739

Figure 8.   Log Periodic Dipole Array with Parasitic Elements --
Single Parasitic Element Design ($\tau = 898$, $s/\ell = 0.113$).

Figure 9.   Impedance of a Log Periodic Dipole Array with Parasitic
Elements ($\tau = 0.898$, $s/\ell = 0.113$).

Figure 10.   E-plane Radiation Power Patterns of a Log Periodic
Dipole Array with Parasitic Elements ($\tau = 0.898$, $s/\ell = 0.113$).

5.2   -- Continued.

first parasitic element of 43 percent of the distance along a cell as measured
from the shortest driven element in that cell, and a spacing for the second
element of 68 percent of the distance along the same cell.   The antenna of
this design is shown in Figure 11.   The original spacing between the driven
elements is unchanged from the initial model and is spaced in accordance to
the geometric ratio, $\tau = 0.95$.   It can be seen from Figure 11 that the log
periodic configuration is maintained from cell to cell and that the antenna is
no longer periodic from element to element.

The measured radiation power patterns in the electric field plane of the
antenna are shown in Figure 12.   The radiation pattern shape is constant
with frequency and has half-power beamwidths of 50 degrees in the E-plane
and 60 degrees in the H-plane (not shown).   Gain measurements greater than
10 db above isotropic were obtained on this model.   One of the most signifi-
cant improvements of this antenna as compared to the same antenna with only
a single parasitic element per cell is an increase in the front-to-back ratio.
An improvement of 5 db or greater is achieved, giving a front-to-back ratio
equal to or greater than 20 db.

63070509

Figure 11.   Log Periodic Dipole Array with Parasitic Elements --
Dual Parasitic Element Design.

500 MC   550 MC   600 MC   650 MC

700 MC   750 MC   800 MC   850 MC

Figure 12.   E-plane Radiation Power Patterns of Log Periodic.

6.   LOG PERIODIC MONOPOLE ARRAY WITH PARASITIC
                      ELEMENTS.

Because of the nature of the transmission-line feeder used with the conven-
tional log periodic dipole array, the antenna cannot be imaged exactly over
a ground plane to form a log periodic monopole array.[9] As a result, it
became necessary to develop techniques for introducing the proper amount
of phase shift between the monopole elements required for log periodic
operation.[10] Successful operating models of log periodic monopoles are
now in existence, but none of these antennas result in a configuration that
conforms to a true image of the log periodic dipole array.

In this respect, the log periodic dipole array with parasitic elements lends
itself to imaging with a ground plane to form a monopole array with para-
sitic elements. Figure 13A shows the current directions on the forward
section of the log periodic dipole array with parasitic elements. The lower
figure (Figure 13B) shows half of this antenna over a ground plane and its
current distribution over the same region of the antenna as Figure 13A.
The current along the transmission-line feeder of the monopole array has
an image in the ground plane with the current direction reversed. The
driven elements of the monopole are connected to the feeder line. For this
arrangement, the image consists of monopole elements connected to the
imaged feeder line. The current in these imaged elements is in the same
direction as the actual elements themselves. The parasitic monopole
elements are connected to the ground plane, and the image of these elements
connects with the actual elements to form an equivalent continuous element
with a unidirectional current distribution. Therefore, it can be seen from
Figure 13 that the monopole antenna and its image, along with the removal
of the ground plane, corresponds exactly to the dipole form of the antenna
with parasitic elements.

6.1   UHF Model.

A UHF model of the log periodic monopole array with parasitic elements
(see Figure 14) was constructed for evaluation. This antenna consists of a
metallic ground plane over which is placed a transmission feeder line.
This line is fed with the inner conductor of a coaxial line as shown in Figure
14. The outer conductor of the coaxial line makes electrical contact with
the surface of the ground plane. The driven elements are attached to the
feeder line, and the parasitic elements are placed in between the driven
elements and electrically connected to the ground plane. A design ratio,
τ, of 0.886 was used for this UHF model, and an element-spacing-to-
element-length ratio, s/ℓ, of 0.0568 was used.

CURRENT DIRECTION

A. DIPOLE ARRAY WITH PARASITIC ELEMENTS.

GROUND PLANE

IMAGE

B. MONOPOLE ARRAY WITH PARASITIC ELEMENTS.

Figure 13.   Comparison of Log Periodic Dipole and Monopole
Arrays with Parasitic Elements.

- 23 -

Figure 14.   Log Periodic Monopole Array with Parasitic Elements.

6.1   -- Continued.

The VSWR of the antenna was measured with respect to 50 ohms for different transmission-line-to-ground-plane spacings. The following configurations were tried:

(a)   uniform transmission-line-to-ground-plane spacing (1/16 inch), and uniform transmission-line-to-parasitic-element spacing (1/16 inch);

(b)   uniform transmission-line-to-ground-plane spacing (1/16 inch), and tapered transmission-line-to-parasitic-element spacing (tapered from 1/16 inch at feed end to 3/16 inch at opposite end);

(c)   tapered transmission-line-to-ground-plane spacing (tapered from 1/16 inch at feed end to 3/16 inch at opposite end), and uniform transmission-line-to-parasitic-element spacing (1/16 inch).

The results of the VSWR measurements as a function of frequency for these various configurations are shown in Figure 15. A good match is shown to exist between the antenna and the coaxial line feed for all three configurations. It is important to note that the VSWR is nearly insensitive to the variations in the transmission-line-to-parasitic-element spacings. This behavior serves as evidence that the parasitic elements are excited by mutual coupling effects rather than by capacitive coupling.

This antenna operates in a pseudofrequency independent manner. A few of the measured E-plane and H-plane (20-degree conical cut) radiation power patterns of this antenna are shown in Figures 16 and 17. It can be seen that the radiation-pattern shapes remain essentially constant with frequency. The half-power beamwidths are 38 degrees in the E-plane and 120 degrees in the H-plane. These radiation patterns have a front-to-back ratio of 15 db.

In its simplicity of feeding, this antenna has the advantage over other log periodic monopole designs. No balun transformer is required, no critical spacing between the transmission-line feeder and the ground plane or parasitic elements exists, and no capacitive coupling to the elements is involved.

A second model of the monopole array with parasitic elements was constructed using a smaller value of τ and a larger value of s/ℓ. A value of τ equal to 0.807 and s/ℓ equal to 0.104 was used. This antenna did not operate in a frequency-independent manner. There was radiation pattern breakup at the frequencies where the main source of radiation appeared at the parasitic

Figure 15. VSWR vs. Frequency for a Log Periodic Monopole with Parasitic Elements ($\tau = 0.886$, $s/\ell = 0.0568$).

Figure 16.   E-plane Radiation Power Patterns of a Log Periodic
Monopole Array with Parasitic Elements ($\tau = 0.886$, $s/\ell = 0.0568$).

800 MC   900 MC   1000 MC

Figure 17.   H-plane Radiation Power Patterns of a Log Periodic
Monopole Array with Parasitic Elements (20-degree conical cut)
($\tau = 0.889$, $s/\ell = 0.0568$).

6.1   -- Continued.

elements. The results of this experiment showed that the mutual coupling
between the parasitic element and driven element was too low, thus indica-
ting that there is a lower limit to the value of τ that can be used with this
class of antennas.

An additional experiment of interest was performed where the parasitic
elements of the first antenna discussed in this section were disconnected
from the ground plane. This configuration of the antenna failed to work in
a frequency-independent manner.

6.2   Microwave Model.

A microwave version of the log periodic monopole antenna with parasitic
elements was designed to operate from S-band through X-band frequencies.
A design ratio of 0.889 and element-spacing-to-length ratio of 0.0557 was
used. The antenna itself was etched on a double clad printed circuit board
with the driven elements and the feeder line etched on one side, as shown
in Figure 18A. The connection at the feed can be seen in this illustration.
The parasitic elements are etched on the opposite side and are shown sold-
ered to the ground plane in Figure 18B. The longest element of the antenna
is 1.556 inches in length and the shortest element is 0.191 inches in length.
A modified connector was used for the feed which stepped the type-N coaxial
size to a subminiature coaxial size while maintaining a 50-ohm character-
istic impedance. This was done to prevent radiation from the feed itself.

The characteristics of this antenna were measured and found to be pseudo-
frequency independent. An impedance circle of about 50 ohms with a VSWR
of 3:1 was measured from 1.5 Gc to 12.6 Gc. Radiation-pattern measure-
ments were also obtained over this frequency range. Some of the E-plane
and H-plane (20-degree conical cut) radiation-power patterns are shown in
Figures 19 and 20. These radiation patterns have essentially constant
beamwidths with a constant vertical take-off angle over the entire frequency
range and with a front-to-back ratio of about 15 db. The serrations in the
radiation patterns are primarily caused by the limited ground plane on which
the antenna was mounted for the measurements.

This log periodic antenna is well suited for microwave applications in that
it provides good electrical performance in this frequency range and is
inexpensive to construct. Good performance is possible primarily because
of the simplicity of feeding the antenna. No special coaxial transformers
are required, and there is no need for coaxial lines or other components in
the vicinity of the element (such components would be a large percentage of

- 29 -

61120812

Figure 18.   Microwave Model of a Log Periodic Monopole Array with Parasitic Elements ($\tau = 0.898$, $s/\ell = 0.0557$).

61120813

Figure 18.   -- Continued.

Figure 19. E-plane Radiation Power Patterns of a Log Periodic Monopole Array with Parasitic Elements ($\tau = 0.898$, $s/\ell = 0.0557$).

Figure 20. H-plane Radiation Power Patterns of a Log Periodic Monopole Array with Parasitic Elements ($\tau = 0.898$, $s/\ell = 0.0557$).

6.2   Continued.

the size of the smallest element). The independence from any form of capacitive coupling eliminates the need for critical spacings.

7.   CONCLUSION.

The log periodic dipole and monopole arrays with parasitic elements have
been introduced and their characteristics presented. It was shown that the
method of feeding these antennas is relatively simple, thus making the
antennas suitable for frequency ranges that are difficult to cover with other
log periodic antennas. It was also shown that an antenna having more than
one parasitic element between each driven dipole element will work as a
pseudo frequency-independent antenna. In this respect, there exist numer-
ous configurations and possibilities with the dipole or monopole arrays
having multiparasitic elements. A limitation on the log periodic dipole or
monopole array with parasitic elements is that larger values of τ must be
used in comparison with other log periodic antennas. As a result, this
antenna will always have a high density of elements.

It appears probable that a log periodic Yagi antenna design might evolve
from the log periodic dipole array with parasitic elements. In the multi-
parasitic element design discussed above, the apparent source of radiation
appeared to be confined to the cells of the antenna rather than to the indivi-
dual elements themselves. This effect occurs when the cells, not the
elements, are log periodic in nature. The cells of this antenna can be made
to conform to a Yagi antenna design. It is conceivable that a log periodic
antenna of this design can be made to work satisfactorily, and further
experiments to investigate this are necessary.

8. REFERENCES

1. D. E. Isbell, "Log Periodic Dipole Arrays", IRE Trans. on Antennas and Propagation, Volume AP-8, No. 3, May, 1960; pp 260-270. (UNCLASSIFIED publication)

2. R. Mittra, "Theoretical Study of a Class of Logarithmically Periodic Circuits", Technical Report No. 59, Antenna Laboratory, University of Illinois; July 1962. (UNCLASSIFIED publication)

3. P. E. Mayes, G. A. Deschamps, and W. T. Patton, "Backward-Wave Radiation from Periodic Structures", Technical Report No. 60, Antenna Laboratory, University of Illinois; December 1962. (UNCLASSIFIED publication)

4. A. A. Oliner, "Leaky Waves in Electromagnetic Phenomena", Research Report No. PIBMRI-1064-62, Polytechnic Institute of Brooklyn; August 1962. (UNCLASSIFIED publication)

5. R. Mittra and K. E. Jones, "Theoretical Brillouin (k-β) Diagram for Monopole and Dipole Arrays and Their Application to Log Periodic Antennas", 1963 IEEE International Convention Record, Part 1; 25-28 March 1963, pp 118-128. (UNCLASSIFIED publication)

6. E. Hudock and P. E. Mayes, "Propagation Along Periodic Monopole Arrays", 1963 PTGAP Internation Symposium; 9-11 July 1963; pp 127-132. (UNCLASSIFIED publication)

7. C. T. Elfving, "Design Criteria for Log Periodic Antennas", 1961 WESCON, Paper 1/2; 22-25 August 1961. (UNCLASSIFIED publication)

8. H. Jasik, "Antenna Engineering Handbook", McGraw Hill Book Company, Inc.; 1961; pp 5-6 to 5-11. (UNCLASSIFIED publication)

9. P. Toulios, "RFD Antenna Techniques Survey" (U), Final Report, Volume 1, Armour Research Foundation of Illinois Institute of Technology, Chicago, Illinois; 19 December 1961. (SECRET publication), pp 65-72.

10. D. G. Berry and F. R. Ore, "Log Periodic Monopole Array", 1961 IRE International Convention Record, Part I; 20-23 March 1961; pp 76-85. (UNCLASSIFIED publication)

(iv + 36)

AD   Accession No.   Copy No.

UNCLASSIFIED

Electronic Defense Labs., Mountain View, Calif.
LOG PERIODIC DIPOLE ARRAY WITH PARASITIC
ELEMENTS -- Normand Barbano. Technical Memo-
randum EDL-M623, 30 January 1964 (Contract
DA 36-039 AMC-00088(E)) UNCLASSIFIED Report.

The design and measured characteristics of dipole
and monopole versions of a log periodic array with
parasitic elements are discussed. In a dipole array
with parasitic elements, these elements are used
in place of every alternate dipole, thereby elimina-
ting the need of a twisted feed arrangement for the
elements to obtain log periodic performance of the
antenna. This design with parasitic elements lends
itself to a monopole version of the antenna which has
a simplified feeding configuration. The result is a
log periodic antenna design that can be used from
high frequencies through microwave frequencies.

1. *Log
2. *Periodic
3. *Dipole
4. *Array
5. *Parasitic
6. *Element
7. Spacing
8. *Monopole
9. *Antenna
10. Two
11. Wire
12. Feeder
13. Phase
14. Brillouin
15. Radiation
16. Pattern
17. Forward
18. Backward
19. Wave
20. Backfire
21. Fire
22. Impedance

UNCLASSIFIED   Copy No.
23. Ultra-High-Frequency
24. Microwave
25. Transmission
26. Line

I. Barbano, Normand
II. Contract DA 36-039
    AMC-00088 (E)

8.1: 8.6

UNCLASSIFIED   Copy No.
23. Ultra-High-Frequency
24. Microwave
25. Transmission
26. Line

I. Barbano, Normand
II. Contract DA 36-039
    AMC-00088 (E)

8.1: 8.6

UNCLASSIFIED   Copy No.
23. Ultra-High-Frequency
24. Microwave
25. Transmission
26. Line

I. Barbano, Normand
II. Contract DA 36-039
    AMC-00088 (E)

8.1: 8.6

UNCLASSIFIED   Copy No.
23. Ultra-High-Frequency
24. Microwave
25. Transmission
26. Line

I. Barbano, Normand
II. Contract DA 36-039
    AMC-00088 (E)

8.1: 8.6